



# PORTAGIG™

## FIREWIRE 800

## Tiny. Bus Powered. Go.

The PortaGig hard drive makes portable recording and editing easy. With its tiny bus-powered enclosure, it's small enough to fit into a pocket, and powerful enough to support high track-count audio sessions. With FireWire 800 and USB 2.0 interfaces, PortaGig 800 is compatible with Mac, Windows and Linux systems supporting FireWire or USB. Designed with a fanless, light aluminum enclosure, it allows you to work on the road easily and reliably. If bus power is not available or is insufficient, you can use the included power supply.

## Features:

- Up to 500GB in a tiny enclosure
- 7,200 and 5,400 RPM models available
- Solid State Disk models available
- Weighs less than 10 Ounces
- All models Tested and approved with Digidesign Pro Tools™ to support over 70 tracks of 24bit / 48k audio, with edits
- SSD supports 128 tracks at 24bit / 48k
- Small, portable, aluminum case
- Runs quietly with fanless design
- Applications: Field recording, storing and exchanging A/V, graphics, prepress, and desktop publishing files.
- Includes universal power supply
- Included carrying case

## Specs:

- **Capacity (7,200 + 5,400 RPM):** 160GB, 250GB, 320GB, 500GB
- **Capacity (Solid State Drive):** 64GB, 128GB, 256GB
- **Interfaces:** (2) FireWire 800 and (1) USB 2.0
- **Bridging Chip:** Oxford 934
- **Average read seek time (HDD models):** 8 msec
- **Average read seek time (SSD models):** 0.1 msec
- **Max Transfer rate (FireWire 800):** 800 Mb/sec (100 MB/sec)
- **Sustained transfer rate (HDD):** up to 76 MB/sec
- **Sustained transfer rate (SSD):** up to 85 MB/sec
- **Dimensions (HxWxD):** .86" x 3.3" x 5.2" inches
- **Weight:** 0.6 lbs for HDD, 0.5 lbs for SSD
- **Power supply:** universal auto switching 100-240V
- **Requirements:** Mac OS 8.6/9.x/10.x, Windows 2000/XP/Vista
- **Format:** HFS+, can be formatted for other OS
- **Approvals:** CE
- **Warranty:** 3 Years, 1 Year Overnight Advance Replacement
- **Includes:** FireWire 800 (9pin to 9pin) cable, USB cable, sleeve, power supply. Manual is downloadable from Glyph web site.

www.glyphtech.com  
800-335-0345

